



Product MUST be turned off throughout this process.
This product must be installed by a qualified electrician in accordance with all national and local electrical and construction codes.



Failure to comply with the installation instructions can result in serious injury or death.

1 Removing MaxiLED Globe from festoon



- (a). Ensure power is Switch off to the festoon.
- (b). Wearing gloves, hold the base of the festoon and the Globe in each hand.



- (c). Twisting the globe in an anti-clockwise direction, remove the globe from the festoon.
- (d). With the globe removed from the festoon. The grommet must be retained.

2 Removal of LED connection board



- (a). Without pulling on the wires, pull on the connection board to remove from the existing festoon.



- (b). The connection board should slide out of the festoon housing.
- THE GROMMET SHOULD NOT BE REMOVED.**

3 Replacing NEW LED



- (a). Find the correct fitting that corresponds to the replacement globe.
- NOTE**
Example: Globe 7, to replaced with replacement globe 7.



- (b). Place connection board into festoon housing.
- (LED IS NOT POLARITY SENSITIVE. I.E.THE LED CAN BE INSERTED EITHER SIDE)**

4 Replacing Globe to the festoon



- (a). Check the grommet is secure on the globe neck.
- (b). Check the connection board is fully inserted into the festoon housing.
- (c). Make sure no cables are loose or trapped in the globe neck.



- (d). Visually check the seal has not been trapped and is in good condition. In a clockwise twisting direction, lock and click the globe to the festoon cable.
- TWIST THE GLOBE TILL YOU CAN FEEL A 'CLICK' THIS WILL ENSURE A IP68 SEAL.**